

## MDC

### WIRE STRIPPERS WITH BUILT-IN VOLTAGE DETECTION FOR PRECISE, FAST AND SAFE STRIPPING

- Fit for all standard round cables from 4mm – 28 mm.
- The cutting depth can be adjusted with the tuning knob so that the insulators do not get damaged.
- Dismantling may be performed all around or in length, thanks to the perfect, self turning knife.



## MULTISTRIIP DETECT

### GENERAL INFORMATION

MULTISTRIIP DETECT is a wire strippers with built-in voltage detection that can show voltages from 50 volts to 600 volts without direct contact to the inner conductor. The cutting depth can be accurately adjusted with the tuning knob in

order to exclude damage to the inner conductor. The built-in voltage detection detects cable separations, hidden wires and even breaches the mains voltage field. MULTISTRIIP DETECT dismantles 4mm to 28 mm cables all around or in length.

### TECHNICAL INFORMATION AND PACKAGING

Reach of detection: 50-600 V.  
 Reading:  
 mains voltage = lights up  
 no mains voltage = no light  
 Reach of frequency: 50-60 Hz.

Battery: 2 \* 1.5 V button cell battery  
 Reach of temperature: 0°C - 40°C.  
 Detects through: wood, construction bricks, autoclaved aerated concrete,...

### APPLICATION AND USE

- **DISMANTLING**  
 Open the cover and insert cable. Push cable against the 'swivel-blade' and close cover.  
 - Turn 1 or 2 times.  
 - Cut in length and dismantle the wrapping.  
 - Adjust cutting depth by turning the screw underneath the handle.  
 Reach of dismantling: from 4mm – 28 mm.
- **TESTING**  
 Activate the mains voltage tester by pushing the ON-OFF button (3 sec).  
 When the LED-lights blink slowly, the MULTISTRIIP DETECT is ready for use.  
 Near dangerous amperage from 50 v- 600 v the LED lights blink fast.  
 After approx. 10 min the mains voltage tester disconnects itself automatically.  
 By holding the ON-OFF switch the mains voltage tester can be switched of.
- **REPLACING BATTERIES**  
 When the mains voltage tester gives no signal, it's time to replace the batteries.  
 Open the device with a screw driver and remove the battery tray.  
 Replace the used batteries by new ones type LR44 1,5 V. while taking into account the polarity.  
 Reinsert the battery tray into the device.
- Detecting built-in or hidden cables, transformers and appliances under mains voltage.  
 Detecting defects in extension cords.  
 Speeds up tests of bifilar light switches.  
 Detecting of hidden multiple sockets, cable boxes,...

Article nr	Name	Content	Section
N861010	Multistrip Detect	1pc.	TOOLS



### NOTICE

All information including images are given with the greatest care. Still, it is appropriate to users regardless of the test the suitability of each product for their own purposes. Novatio is not liable for the completeness and accuracy of information and refuses warranty for your specific use. The guarantee, which Novatio products provide, relates only to the standard conditions of sale of this product. In no case Novatio can be held responsible for incidental damages, or damages for improper use or sale of the product to another customer.



TOOLS

WWW.TECH-MASTERS.EU

